

# COLOR TOUCH SCREEN CONTROLLER (CTP)

## OPERATIONAL GUIDE



**Color Touch Screen Controller with Power Supply:** Programmable DMX lighting controller for RGB fixtures. Lighting effects can be accessed and modified with the touch sensitive screen. Built in clock and calendar allows scheduled events to trigger custom lighting effects. Comes ready to mount onto a standard U.S. single gang switch box or two gang wall box. A 9VDC Power Adapter is included and fits discreetly inside the Junction Box behind the controller.

**Compatible With:** Remote Dynamic Color Changing Power Supplies with DMX.

- A** A Blue LED is used to indicate whether the unit is on or off.
- B** Buttons 1-8 are used to select individual scenes. Scenes can be static or dynamic. Double pressing buttons 1-8 will reset the Dimmer, Speed, and Color to default.
- C** Used to cycle between 25 different pages (A, B, C, D, E x5). In combination with buttons 1-8, 200 different scenes can be stored.
- D** The select button allows you to cycle through the Dimmer, Speed, and Color fader controls. The fader at the bottom of the unit is used to select the intensity of the Dimmer, Speed, and Color settings.
- E** The green LED indicates that the Dimmer, Speed, and Color settings on the STICK are set to default. If the fader is moved to the right or left of the default (green), one of the 8 blue LED's will indicate your current intensity level.
- F** The colorized fader offers a direct access to basic colors with a simple touch.