

INSTALLATION INSTRUCTIONS FOR

VEGA ROUND & OVAL

- This product is ETL listed.
- This product is suitable for indoor dry locations only.
- This product can mount to either a 4" square electrical box with round plaster ring or an octagon electrical box.
- Can be dimmed with a standard incandescent dimmer.

CAUTION-RISK OF FIRE

This product requires installation by a qualified electrician.
Before installing, be sure to read all instructions and
TURN THE POWER TO THE ELECTRICAL BOX OFF.


STEP 1

Attach crossbar to junction box with screws facing down. Pass 120V supply wires through center hole in fixture mounting plate then attach mounting plate to screws on crossbar using thumb nuts provided.



STEP 2

Use allen wrench to loosen set screws holding suspension cables and adjust to desired height, then retighten set screws. Excess suspension cable can then be cut off.



STEP 3

Extend fixture cord coming from fixture up to the junction box and attach 120V supply wires with wire nuts provided. If necessary push any excess cord through center hole into junction box.



STEP 4

Slide cover up to the mounting plate and position it so the three magnets hold it securely in place.



STEP 5

This step is done easier with 2 people. While one person holds glass assembly, slide socket assembly up suspension cables enough to allow suspension ring to be inserted through hole in glass and centered.



STEP 6

Hook safety cables attached to glass assembly to eyelets on suspension ring.



STEP 7

Insert 2 150W max bulbs and position socket assembly on top of the glass assembly.

INSTALLATION