

REV.04.20.15



Monorail Canopy Mount LED Kit with 60W 12V electronic transformer includes everything you need for a complete system — just add fixtures. Kit includes electronic 60 watt 12 volt transformer, Monorail, appropriate quantities of 1" standoffs for every 3 feet of rail and 2 pairs of end caps. Fast acting circuit breaker on low voltage side of transformer will shut the system off in case of overload or short and can be easily reset. Satin nickel, polished nickel or antique bronze finish.

Length:

4, 8, 12, 16, 20, 24, 28 or 32 feet
 1.2, 2.4, 3.7, 4.9, 6.1, 7.3, 8.5 or 9.8 meters

Dimming:



With low voltage electronic dimmer - Lutron Diva DVELV-300P recommended

Standard Mounting:

Rail mounts 1" (2.5cm) from ceiling.

Finish:

Satin Nickel, Polished Nickel or Antique Bronze



Transformer Type	Wattage	Voltage Output	Monorail Length (ML)	Finish
MTE	60L	12	K4	SN
MTE Monorail Canopy Mount Electronic Transformer	60L 60 Watt LED	12 12 Volt Single Feed	K4 Kit with 4' Monorail K8 Kit with 8' Monorail K12 Kit with 12' Monorail K16 Kit with 16' Monorail K20 Kit with 20' Monorail K24 Kit with 24' Monorail K28 Kit with 28' Monorail K32 Kit with 32' Monorail	SN Satin Nickel PN Polished Nickel BZ Antique Bronze

PROJECT:

FIXTURE TYPE:

DATE:

